



100W70T 70V Transformer

Our 100W70T is an 70V matching line indoor audio transformer that converts the primary voltage of a PA or audio amplifier from 70V to 8 ohms or 4 ohms to eliminate power loss caused by long distance runs between the amplifier and speaker. Our audio transformer offers full range frequency response, 20Hz to 20kHz (plus minus 1dB), for no insertion loss or effect on sound quality. This includes 100W, 80W, 60W, 40W, 20W taps that allow different power levels and volume for each speaker. Six-inch cable leads give you plenty of room to work around, and the 100W70T includes a self-adhesive pad for quick and easy installation.

SPECIFICATIONS

Primary voltage: 70V
Power handling: 100W
Primary taps: 100W, 80W, 60W, 40W, 20W
Frequency Response 20Hz to 20kHz plus/minus 1dB

Insertion loss: 1 dB
Secondary impedance: 8 and 4 ohms
Mounting dimensions: (W x D x H) 3.37" X 2" X 2"