



NERO MAX8 Multi-Zone Amplifier

The NERO MAX8 is a highly efficient Class D multi-channel audio distribution system that powers up to four zones with up to six different sources for residential and commercial audio systems. Highly compatible and expandable this amplifier is engineered with cutting-edge features including full control from iOS and Android devices. The free App duplicates the optional control keypads and allows you to select zones, adjust volume, treble and bass, directly through a smart device.

The NERO MAX8 includes numerous input sources including four stereo line-level RCA, one 3.5mm aux, and one optical/3.5mm combo analog source input. In addition, RS232 and ethernet ports allow transferring and receiving the serial data between home automation systems.

SPECIFICATIONS

- Power: 8 Ohm - 40W x 2 per zone 4 Ohm - 80W x 2 per zone
- Bridge: 8 Ohm Only - 80W
- S/N: >85dB A WTD
- THD: <0.1%
- Freq Response: 20Hz-20KHz
- Input Impedance: >47 K Ohm
- Output Impedance (line level) 100 Ohms
- Input Sensitivity: 250mv
- Protection: Overload, Short Circuit, Temperature
- System Voltage: DC +12V
- External Mute and TRIGGER OUT Voltage: DC +12V
- Network Connector: RJ45, Standard 10/100Mb
- Power Supply: AC 115V/60Hz
- Output Connection: Terminal Block
- Dimensions: 16.9" W x 3.5" H x 16.4" D
- Weight: 19lbs
- Warranty: 2 Years